

1 IR-200 Remote



	TV Power Button
	STB - Standby, Power ON/OFF
	Source
	Source Volume + / Volume -
	Favourite Channels
	Search
	Server Settings
	To view categories when in Live TV/EPG/TV Series/VOD Menus
	Live TV
	Video On Demand
	TV Series
	Personal Video Recorder
	Menu
	Guide
	Arrow Keys / OK
	Back
	Home
	Pointer
	Volume - Up (+) / Down (-)
	Information
	Last Channel
	Channel - Up (+) / Down (-)
	Rewind
	Play/Pause
	Fast Forward
	Record
	Stop
	Mute
	Red Button
	Green Button
	Yellow Button
	Blue Button
	Number Pad
	Page Down PG+ Page Up

2 IR-200 Remote - Learning Function

The learning function on the IR-200 remote is used to control your TV. You will be able to control: Power ON/OFF, Volume and Input Source. To do this you will need the factory remote control for your TV.



1. On the IR-200, press and hold the TV POWER + OK buttons for 3 seconds. Once the red light turns on, release the buttons.

2. Press the learning key you would like to program (TV POWER/ SOURCE/ VOL+/ VOL-) and the red light will start flashing. The flashing red light indicates the IR-200 is in learning mode.



3. Align your TV Remote and the IR-200 so that the front transmitters are pointing at each other. They should be within 1 inch or 3 cm of each other.

4. After receiving a learning function successfully, the red light will blink 4 times.

5. To learn other keys, repeat Steps 2-4

6. After learning, long press the OK key for 3 seconds, and the red light will blink twice to save learning.

Note:

If you do not select the key within 15 seconds after entering the learning state, it will automatically exit the learning state.

Please note not all TVs are compatible with source pairing

CEC settings to support the IR-200, your TV & your BuzzTV Box

If you were successful in TV source pairing the IR-200 to your TV then you need to make sure the CEC settings on both the TV and your BuzzTV Box are enabled and in some cases in the correct HDMI port on the TV, refer to your TV manual if needed. (Initially set to ON)